

快换模块

信号线航空接头

快换配件·机器人端固定型专用

机器人末端



代码	类型	材质	
		绝缘体	护套
WQC06	信号线航空接头	PVC	

特点：与快换信号模块搭配使用，含线材。





规格：1

R(机器人端)





T(工具端)





规格：2

R(机器人端)

信号通道数：12




T(工具端)





R(机器人端)

信号通道数：19





T(工具端)




规格：3

R(机器人端)





T(工具端)





规格：4

R(机械手端)



T(工具端)



视角标准：第一视角

代码	型号	规格	安装位置	信号通道数	线长(m)	A	B	电压范围(V)	最高电流(A)	适配信号模块型号
WQC06	1(手动快换)		R(机器人端)	9(9芯)	3	50±1	9.2±1	0~250	0.5	WQC05-1-R-9
			T(工具端)		1.5		8±1			WQC05-1-T-9
	2(工业机器人快换)		R(机器人端)	12(12芯)	3	44±1	Ø30±1		12芯：2 19芯：1	WQC05-2-R-12
			T(工具端)	19(19芯)	1.5					WQC05-2-T-19
	3(协作机器人快换)		R(机器人端)	9(9芯)	3	36.2±1	Ø7±1	0~250	0.5	WQC05-3-R-9
			T(工具端)		1.5					WQC05-3-T-9
	4(协作机械手快换)		R(机械手端)	9(9芯)	3	50±1	9.2±1		0.5	WQC05-4-R-9
			T(工具端)		1.5		8±1			WQC05-4-T-9

① 机器人端和工具端的信号通道数需一致。



请按图示订货

代码	规格	安装位置	信号通道数
WQC06	1(手动快换)	R(机器人端)	9(9芯)
		T(工具端)	

WQC06—1—R—9



未标价(元)

● 优惠价

数量	1~5	6~
价格	100%	另行报价



交货期

5